

## Glancetron 2010

Scanner with integrated counterfeit money detector



- CCD touch scanner for bar codes
- With integrated tester for counterfeit money
- Elegant slim line housing
- 80 mm scanning width, 100 scans per second
- Configurable integrated buzzer

### Specifications

General	
Output Interface	PS2, USB, RS232C
Read Barcode Format	EAN-8, EAN-13, UPC-A, Code32, UPC-E, EAN/UPC, Add-on, Code-39, Code-11 UCC/EAN/Code 128, Industrial-25, Interleaved-25, Matrix-25, Cina Post-25, Codabar/Nw7 MSI/Plessey
Resolution	Min. 0.127 mm (5mil.)
PCS	Up to 0.45
Windows width	80mm
Read barcode size	110mm
Depth of field	0-50mm (0.39 - 15.6mil. PSC=9)
Light source	Red LED 630nm
Read Sensor	CCD linear image sensor
Scanning Rate	100 Scans/sec
Read Indicator	Red LED and adjustable-volume-buzzer
Programmi	by user manual or download via RS232C
Cable	2m straight type
Weight	95g (without cable)
Drop Durability	1m drop onto concrete surface
Working Temp.	0-50 C°
Working Humidity	10-90% RH
Storage Temp.	-10-60 C°
RFI/EMI	FCC Class A& CE
Voltage	DC 5V +-5%
Working Power	20uA (0.02mA)
Specification	Interface cables are interchangeable.
Remark	Plug & Play USB barcode reader works on Windows 98, 2000, XP, Macintosh, Linux and any other system with USB keyboard support

Your Dealer